

# LFX Master DMX

## The advanced flicker box



Create natural looking lighting effects of fire, TV, welding & more.

- three output channels
- HD flicker presets (24 fps)
- device presets for easy set-up
- DMX-512 OUT and IN
- arbitrary DMX address patching
- optional battery operation

It has never been that easy to create LFX using LED, tungsten and fluoros.

**miE**  
movie-intercom  
LightingFX Tools

movie-intercom  
Bluecherstr. 21  
10961 Berlin  
Germany  
call +49-30-2232 0575  
info@movie-inter.com

[www.movie-inter.com](http://www.movie-inter.com)

# LFX Master DMX

- Multi-tool
- HD LFX
- NEW

## Specs

### General

<i>output channels</i>	three
<i>operation voltage</i>	6 - 32 VDC, 200 mA, PSU included
<i>temperature range</i>	-10...65°C (14°F...149°F)
<i>dimensions</i>	200 x 110 x 86 mm
<i>weight</i>	650 grams (1.4 lbs) w/o PSU
<i>DMX sockets</i>	5-pin XLR
<i>DMX protocol</i>	USITT DMX-512-A



### HD effect presets

fire, candle, TV, welding, broken fluoro, strobe

<i>resolution preset</i>	24 fps on default value
<i>transitions</i>	shapes edges of a curve hard, medium or soft

### Device presets

Pre-defined DMX set-up for **Kino Flo**: FreeStyle LED, Select LED, Diva-Lite LED, Celeb LED, Parabeam, **Arri**: SkyPanel, L5-C, L7-C, L10-C, Broadcaster 2+, generic 2-channel LED device, 12-channel tungsten dimmer; custom DMX channel allocation for all others

### DMX output

*Channel range* 001 - 512

Patch any LFX Master channel to any DMX address. Set fixed DMX channels for CCT, G/M, gel and RGB.

### DMX input presets

Extend the functionality with a dimmer board and presets.

- Separate dim (max & min) control for CH 1, 2, 3 using a 6 channel dimmer board
- remote control via DMX for all effects

Use the LFX Master DMX as an inline device in an existing DMX universe.

all specs subject to change without prior notice, V2017-7