

SUPPORT - Connectivity Guide

compatible LED lamps, controllable by the LFXHub



Please find the latest list on www.movie-inter.com or send an [eMail](mailto:info@movie-inter.com) .

phone +49 (0)30-2232 0575
 fax +49 (0)30-2232 0571
 web www.movie-inter.com
 mail info@movie-inter.com

Version 03 - Sep 2015

compatible LED lamps, 0-100% dimmable with the LFXHub:

page 1 of 2

fixture	manufacturer	good for effects	DMX Set-up at LFXHub display
<u>Area 48 Soft</u>	Brothers, Brothers & Sons	all effects	At lamp choose "8 Bit mode" , set "Response" time to "fast" (valid for software version 1.4.00) In this mode there is only one DMX channel used. At LFXHub set-up the corresponding DMX channel.
<u>Brute 9</u>	LEDz		LEDz lamps use a single DMX channel. CH1= 001 to 001 CH2= any to any CH3= any to any > change DMX-ID
<u>Brute 16</u>			
<u>Superspot</u>			
<u>Karesslite 6006</u>	Gekko		The Kareslite needs 6 DMX channels. CH1= 001 to 005 CH2= 007 to any CH3= any to any > change DMX-ID
<u>Karesslite 6012</u>			
<u>Karesslite 2036</u>			IMPORTANT: exclude CH 006 as shown above
<u>L5-, L7-, L10-Series</u>	ARRI		Set L7-T to mode 01 -DIMM 8 bit, needs 1 DMX channel; Set L7-C to mode 02- White 8 bit, needs 3 DMX channels; CH1= 001 to 001 CH2= 004 to any CH3= any to any > change DMX-ID
			IMPORTANT: exclude CH 002 and 003 as shown above for mode 02 Please be advised, there are different software versions of this lamp available.
<u>Celeb 200/201/401/401Q DMX</u>	KinoFlo		Celeb 200 DMX needs 2 DMX channels CH1= 001 to 001 CH2= 003 to any CH3= any to any > change DMX-ID
		IMPORTANT: exclude CH 002 as shown above	
<u>1x1 Bicolor</u>	Litepanels	please call Litepanels for DMX set-up, requires a RJ-45 to DMX XLR adapter	
<u>Litepad DL</u>	Rosco	wirelessly linked with the <u>DMX2dim</u> (receiver) and <u>DMXio</u> (transmitter) @ DMX2dim connect at "DIMA" the two wire (polarity!) with adapter or simply cut off the wires	



SUPPORT - Connectivity Guide

compatible LED lamps, controllable by the LFXHub

Please find the latest list on www.movie-inter.com
or send an [eMail](mailto:info@movie-inter.com) .

Version 03 - Sep 2015



phone	+49 (0)30-2232 0575
fax	+49 (0)30-2232 0571
web	www.movie-inter.com
mail	info@movie-inter.com

page 2 of 2

Most LED lamps should be compatible for LFXHub control via DMX.

Please be advised effects generated by the LFXHub might look different depending on the response time pre-programmed within the LED lamp's software. We highly recommend to test each effect with the lamp before you use it live.

It would be more than great if you could inform us if you have been using a lamp successfully with the LFXHub not shown in this list. Movie-intercom does not guarantee the operation of an LED lamp with the LFXHub.