

LFX Master DMX - improved

Spectacular fire effect with shifting colors with SkyPanel-C



phone +49 (0)30-2232 0575
 fax +49 (0)30-2232 0571
 web www.movie-inter.com
 mail info@movie-inter.com

So it works

(Skypanel firmware > 3.0/4.0)

1. Choose DMX OUT preset Arri > Skypanel > GEL > CONFIRM settings
2. Goto "edit channels" > modify the red values, **Dimmer min knob: 20%**
3. Turn EFFECT to position "fire" - that's it.

Connect the Skypanel-C and go ahead! It will look like ...

in the sample clip: <https://www.movie-inter.com/en/lfx-master-flickerbox/dmx/#fire-1ch-skypanel-c>

NEW

LFX Master DMX software version 1.01.3,
 manual set-up (values shown with device preset)

DMX channel	function	Notes	Value
001	Dim	DIM OUT 1	
002	CCT	color temperature	000
003	Filter 1 quality	000 = best	000
004	GEB	Gel brand > Lee Filters	129
005	GEC	Gel category > Color Filters	051
006	GEL	Gel > "Golden Amber"	022
007	Fi1 (X-fade)	DIM OUT 3	
008	Fi2	Filter 2	000
009	CM2	Filter color quality	000
010	GB2	Gel brand 2	129
011	GC2	Gel category 2	051
012	GE2	Gel 2> Light red	162
013	FXT	color fade	000
014	Fan	not used	000
015	Preset	not used	000
016	Reserve	not used	000
017	Reserve	not used	000

change settings in expert mode

Expert mode DMX OUT: address=function	
001	Dim OUT 1
002	>fix 000
003	>fix 000
004	>fix 129
005	>fix 051
006	<fix 022
007	>Dim OUT 3
008	>fix 000
009	>fix 000
010	>fix 129
011	>fix 051
012	<fix 162
013	>fix 000
014	>fix 000
015	>fix 000
016	>fix 000
017	>fix 000
>expert mode	

for new FREE firmware (expected release by end of May):
 These settings will be implemented in the new firmware. No further set-up required.